

Segment Terminals

Segment Terminals are used to create a partial circuit (segment circuit) within a main 24 VDC circuit.



	IC220PWR011	IC220PWR012	IC220PWR013	IC220PWR014
Product Name	Segment Terminal 24 VDC	Segment Terminal Fused 24 VDC	Segment Terminal Fused with Diagnostics 24 VDC	Segment Terminal Electronic Fused 24 VDC
Input Voltage	24 VDC	24 VDC	24 VDC	24 VDC
Input Voltage Range	19.2 - 30 VDC	19.2 - 30 VDC	19.2 - 30 VDC	19.2 - 30 VDC
Maximum Current	8 Amps	8 Amps	6.3 Amps	8 Amps
Overload/Short Circuit in Main Circuit	No	6.3 amp slow blow fuse	6.3 amp slow blow fuse	Electronic Fuse
Surge Voltage/Over Voltage	Protective circuits of the power terminal	Protective circuits of the power terminal	Protective circuits of the power terminal	Protective circuits of the power terminal
Polarity Reversal	Protective circuits of the power terminal	Protective circuits of the power terminal	Protective circuits of the power terminal	Protective circuits of the power terminal
Current Consumption from Local Bus UL (mA)	N/A	N/A	25 mA, maximum	30 mA, maximum
LED Indicators	24 VDC Voltage Present	24 VDC Voltage Present and Blown Fuse	Bus Diagnostics and Blown Fuse	Bus Diagnostics and Blown Fuse
Required Terminal Strip	(1) IC220TBK087 (Contains 10 strips)	(1) IC220TBK087 (Contains 10 strips)	(1) IC220TBK087 (Contains 10 strips)	(1) IC220TBK087 (Contains 10 strips)